



UDB Instruction Manual Rev. 07.02

- ♣ Press the red "ON/OFF" button to turn the Ultimate Dealer Button on and off.
- ♣ Press the "SHIFT" button to begin setting the UDB. The current display area flashes to indicate that it is in set mode. Press the "SHIFT" button again to move the cursor to the next cell.
- ♣ Once the cursor is in the desired display area (i.e. hours, minutes, or seconds of ROUND TIME, SMALL or BIG BLIND, or ANTE), press the "UP" or "DOWN" arrow buttons to set preferred value. Pressing the "DOWN" arrow will decrease values from 999 to 000. Pressing the "UP" arrow will increase values from 000 to 999.
- ♣ Pressing the "UP/DOWN" arrow button once will increase/decrease values by one each time the button is pressed. Pressing AND holding the button down continuously will increase or decrease the values rapidly.
- ♣ There is an optional "K" (representing thousands) for the small/big blind and ante displays. Once the cursor is located in either cell immediately following the small/big blind or ante cells, press the "UP" or "DOWN" arrow to turn the "K" on or off.
- ♣ Once all cells are set to the desired values AND none of them are blinking (The UDB's cells reach a non-blinking state by pressing the shift button once more after the optional "K" cell for the "ANTE" setting.), press the "UP" arrow to advance unit to the next round and repeat steps above to set Rounds 1-10. Once in the non-blinking mode you can use both the "UP" or "DOWN" arrow buttons to go back and forth between round settings. You do not have to utilize all 10 rounds for your tournament. (i.e. If you wish to include only 6 rounds leave all cells set to "0" in Rounds 7-10 before returning to Round 1 to start the UDB.)
- ♣ To pause the timer at any time, press the "START/STOP" button. Pressing it once more will re-start the timer.
- ♣ Once the timer reaches 00:00:00 an alarm will sound to notify you. Press the green "START/STOP" button or ANY lower control button to turn the alarm off. The UDB will automatically advance itself to the next round. Press the "START" button to begin the next round's countdown.
- ♣ The UDB preserves all values when turned off and on again. To clear all values back to "0" remove batteries for a few seconds.

That is it, now shuffle up and deal!